

简体中文

便携高清无损音乐播放器

接口介绍 (图片仅供参考, 具体以实物为准)

4.4mm平衡耳机/线路输出口

3.5mm耳机/线路输出口

6.35mm耳机/线路输出口

电源、锁屏按钮/音量旋钮

显示屏

上一曲键

播放/暂停键

下一曲键

多功能键

侧面氛围灯

4.4mm平衡耳机/线路输出口

3.5mm耳机/线路输出口

6.35mm耳机/线路输出口

电源、锁屏按钮/音量旋钮

Type-C充电/供电端口

TF卡槽

USB HOST端口

光纤输出口

同轴输入/输出口

台机模式开关

HOLD开关

Type-C数据/充电端口

1

简体中文

便携高清无损音乐播放器

开/关机

M27开机状态长按电源按钮开机。首次开机时, 选择相应语言, 点击完成进入主界面; 开机状态下长按电源按钮出现关机提示框, 可选择关机或重启。

充电

M27支持快充, 为达到设计的充电时间, 推荐选用符合PD3.0或以上的充电器。

手势操作

返回上一级: 从屏幕左侧边缘向右滑动, 或屏幕右侧边缘向左滑动
返回桌面: 从屏幕下方上滑
多任务管理: 从屏幕下方上滑并停留

工作模式切换

M27拥有6种工作模式, 分别为安卓模式、纯音模式、USB解码模式、蓝牙接收模式、同轴解码模式和AirPlay模式。首次开机将默认为安卓模式, 您可以在下拉菜单, 或设置菜单中点击工作模式来切换到其他工作模式。

●安卓模式/纯音模式:

安卓模式/纯音模式下可连接电脑与M27传输数据。
注: MAC系统的MTP驱动可通过下载地址: https://www.fioo.com/Driver_Download 进行下载。

●USB解码模式:

首次使用USB解码模式前, 您需要前往官网下载USB DAC驱动, 并按照相应教程安装驱动后方可使用USB解码功能。

●蓝牙接收模式:

首次切换到蓝牙接收模式时, M27将自动进入配对状态, 后续再次进入蓝牙接收模式时将自动回连上一次连接设备。

●同轴解码模式:

切换到同轴解码模式后, 系统会自动将同轴接口切换为输入模式, 此时给M27接入有效同轴信号, M27即可开始同轴解码工作。

●AirPlay模式:

AirPlay模式工作时需要接入WiFi网络, 进入AirPlay前请确认M27已连接正常可用的网络。

台机模式 (D.MODE) 开关功能

开关拨到ON, 台机模式开启, 此时电池将不充电。
开关拨到OFF, 台机模式关闭, 此时电池可正常充电。

2

简体中文

便携高清无损音乐播放器

超级大耳模式

当检测到快充适配器 (推荐12V=3A以上) 插入时, 增益设置会新增“超级大耳模式”菜单。若台机模式开关置于ON, 系统会弹窗提示是否需要启用超级大耳模式, 请根据需要进行选择是否启用。

HOLD开关功能

HOLD开关启用后, 可锁定M27机身按键、显示屏和旋钮的操作响应, 防止误触。您可以在设置-通用菜单下选择需要锁定操作的按键, 或者通过取消HOLD锁定来恢复按键功能。

USB端口

M27底部拥有3个Type-C的USB端口, 功能如下:
左侧的是POWER IN的端口, 仅支持充电/供电功能, 不能连接电脑传输数据;
中间的是USB3.0端口, 支持数据传输、USB HOST、USB OTG以及给M27充电等功能;
右侧的是USB HOST端口, 仅支持USB Audio和USB OTG等功能, 不能给M27充电或者连接电脑传输数据;

固件升级

●OTA在线升级

打开WiFi并连接到可用网络即可自动检测是否有新版本固件更新。若未检测到新版本, 可尝试前往“技术支持-固件升级-在线升级”, 点击“检查更新”进行手动检测更新。

●本地升级

请前往官网下载升级固件, 并按相应教程进行版本升级。
下载地址: <http://www.fioo.com/supports>

注意事项

★请勿将电池置于高温环境中, 电池浸水后禁止使用, 若出现膨胀, 请勿继续使用。
禁止拆解、撞击、挤压、刺破电池或将电池投入火中。
★请勿将设备置于温度过高或过低 (45°C以上0°C以下), 请勿将设备放置在车内等密闭高温环境中。
★不可自行维修、拆卸和将产品放在有水的地方。
★若长期没有使用本产品时, 需要定期给产品充电, 以保证电池寿命。
★当您在使用耳机时, 会因此听不清外界环境声音, 为了您的安全, 请避免在危险环境中使用耳机。
★搭配电压过高的充电适配器充电可能会损坏机器, 请选择推荐使用的充电器进行充电。
★系统发生故障导致死机时, 可尝试长按“电源按钮”10秒以上, 强制重启机器。

3

简体中文

便携高清无损音乐播放器

包装清单 (请核对包装内是否包括以下物品)

●M27主机 ●钢化膜 (出厂贴在主机上) ●皮套 (出厂套在主机上)
●DK1 PLUS底座 ●USB数据线 ●售后维修卡
●快速入门 ●卡针

了解更多

●有关M27的相关视频教程和常见问题解答 (FAQ), 请扫描M27 FAQ二维码;
●了解产品更多信息请访问: www.fioo.com
●了解产品详细使用说明请访问<https://www.fioo.com/supports>下载相关文件查阅;
●在M27的“设置-系统-法律信息”中, 可以查看产品的CMIT-ID

产品名称: 便携高清无损音乐播放器
产品型号: F3051M
额定输入: 5V=3A
尺寸: 约157.4x85.1x28mm
重量: 铝合金约556g, 钛合金约630g
执行标准: Q/FADZ 1-2017
制造厂: 广州飞傲电子科技有限公司
地址: 广州市白云区龙归街发良路21号



由于产品不断改进, 各项规格及设计随时更改, 恕不另行通知。

4

环保材料说明

产品中有害物质的名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr,VI)	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
PCB	×	○	○	○	○	○
PCBA 焊点	×	○	○	○	○	○
元器件	×	○	○	○	○	○
显示屏*	×	○	○	○	○	○
电池*	×	○	○	○	○	○
外观件	○	○	○	○	○	○
配件*	×	○	○	○	○	○

注: 表中标记“×”的部件, 皆因全球技术发展水平限制而无法实现有害物质的替代。带“*”号部件表示如果在您所购买的产品中无该部件, 请忽略表中该部件信息。
○: 表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572-2011规定的限量要求以下。
X: 表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572-2011规定的限量要求。

根据中国电子行业标准SJ/T 11364-2014 和相关的中国政府法规, 本产品及其某些内部或外部组件上可能带有环保使用期限标识。取决于组件和组件制造商, 产品及其组件上的使用期限标识可能有所不同。组件上的使用期限标识优先于产品上任何与之冲突的或不同的环保使用期限标识。

 此环保使用期限只适用于产品在规定的条件下工作

5

English

Portable High Resolution Music Player

Buttons and Ports Labeled (Pictures are for reference only. The actual product may vary)

4.4mm balanced headphone out/line out

3.5mm headphone out/line out

6.35mm headphone out/line out

Power and Lock button/Volume knob

Multifunction button

Display

Previous track

Play/Pause

Next track

Side ambient light

4.4mm balanced headphone out/line out

3.5mm headphone out/line out

6.35mm headphone out/line out

Power and Lock button/Volume knob

Type-C charging/power supply port

microSD card slot

USB HOST port

Optical out port

Coaxial in/out port

Desktop mode switch

HOLD switch

Type-C data/charging port

6

English

Portable High Resolution Music Player

Power On/Off

When the M27 is off, hold the Power button to turn it on. On its first startup, tap the preferred language onscreen to enter the main UI. Hold the Power button while the M27 is on and a shutdown dialogue will pop up. You can select to turn off or reboot the player.

Charging

The M27 supports fast charging. To achieve the designed charging time, it is recommended to use a PD3.0 or above power source.

Gesture Operation

Return to previous menu: Swipe right from the left edge of the screen, or swipe left from the right edge.
Return to homepage: Swipe up from the bottom edge of the screen.
Multitask managing: Swipe up from the bottom edge of the screen and then hold.

Working Modes Switch

The M27 has six working modes: Android mode, Pure Music mode, USB DAC mode, Bluetooth Receiving mode, Coaxial Decoding mode, and AirPlay mode. The M27 will default to enter Android mode when it powers on for the first time. You can switch to other working modes on the drop-down or Settings menu.

●Android Mode/Pure Music Mode

Under the Android mode/Pure Music mode, the M27 can be connected to a computer for data transmission.
Note: The MTP driver for MAC can be downloaded at: https://www.fioo.com/Driver_Download

●USB DAC Mode

Before using the USB DAC mode for the first time, please download the USB DAC driver on our official website and follow relevant instructions to install it.

●Bluetooth Receiving Mode

When switching to the Bluetooth Receiving mode for the first time, the M27 will automatically enter the pairing state. The next time it enters Bluetooth Receiving mode, it will reconnect to the last connected device automatically.

●Coaxial Decoding Mode

After switching to the Coaxial Decoding mode, the system will automatically switch the coaxial port to input mode. At this time, connect the M27 to valid coaxial signals and the Coaxial Decoding mode will be enabled.

7

English

Portable High Resolution Music Player

●AirPlay Mode

The AirPlay mode requires a valid WiFi connection. Please confirm that the M27 is connected to an available network before entering the AirPlay mode.

Desktop Mode Switch (D.MODE)

When switching to ON, the desktop mode is enabled, and the battery will not be charged; when switching to OFF, the desktop mode is disabled, and the battery will be charged.

Ultra High Gain Mode

When a fast charging power adapter (12V=3A recommended) is inserted and detected, the "Ultra High Gain mode" will show up on the GAIN settings menu. Meanwhile, a dialogue prompt of "Switch to Ultra High Gain mode?" will pop up if the D.Mode switch is on, and you can decide whether to switch or not based on your needs.

HOLD Switch

When the HOLD switch is turned on, all buttons on the side of the M27, display screen and the knob will be locked to prevent unintended touches. You can choose the button to be locked on the settings menu, or turn off the HOLD switch to restore the button function.

USB Port

The M27 has 3 USB Type-C ports at its bottom. Here are the functions explained:
• On the left is the POWER IN port, which supports charging and power supply, but not data transfer with computers.
• In the middle is the USB 3.0 port, which supports data transfer, USB HOST, USB OTG and charging.
• On the right is the USB HOST port, which only supports USB AUDIO and USB OTG, but not charging or data transfer with computers.

Firmware Upgrade

●OTA (Over-the-Air) Online Upgrade

Turn on the WiFi function on the M27 and connect it to an available network. It will automatically detect if there is a new firmware. If no firmware is detected, please go to "Technical Support -> Firmware Update -> Online Upgrade" to check and upgrade the firmware manually.

8

English

Portable High Resolution Music Player

●Local Upgrade

Please download the firmware on our website and follow relevant instructions to upgrade it.
Download link: <http://www.fioo.com/supports>

Notes and Precautions

★Please do not put the battery in a high-temperature environment. The battery is prohibited from use if it is soaked in water, or if it gets swollen. Please do not disassemble, hit, crush, or puncture the battery, and do not put it on fire.
★Please do not place the device in circumstances of excessive high/low temperatures (above 45°C or below 0°C), or in an enclosed high-temperature environment, such as in a car.
★Please do not repair or disassemble the device on your own and do not put it in water.
★Please charge the battery on a regular basis to secure the battery life if this device has not been used for a long time.
★You might not be able to hear the sound of the surroundings when using headphones. For your safety, please avoid using headphones in dangerous situations.
★It is recommended to use a suitable charger in case of a high-voltage adapter causing damage to the device.
★In the likely event that the M27 hangs up, you may hold the Power button for over 10 seconds to force a reboot.

List of Items Included (please check if the following items are included)

●M27
●Leather case (applied on the M27 in factory)
●Tempered glass screen protector (applied on the M27 in factory)
●DK1 PLUS heat dissipation dock
●USB data cable
●Warranty card
●Quick start guide
●Ejector pin

9

English

Portable High Resolution Music Player

To Learn More

●For related video instructions of the M27 and FAQ (Frequently Asked Questions), please scan the QR code below.
●To learn more about the product, please visit our website: www.fioo.com
●For detailed instructions of the M27, please visit <https://www.fioo.com/supports>
●To check the CMIT-ID of the M27, please go to the menu of Settings->System->Legal information.

Due to continuous improvement, every specification and design is subject to change at any time without further notice.



WEEE Directive & Product Disposal

 At the end of its serviceable life, this product should not be handed as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Internal/Supplied Batteries:

This symbol on the battery indicates that the battery is to be collected separately. This battery is designed for separate collection at an appropriate collection point.

Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries.



10

English

Portable High Resolution Music Player

Hereby, Guangzhou FIOO Electronics Technology Co., Ltd. declares that this device is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at: www.fioo.com/doc

Function	Frequency	Maximum output power
Bluetooth	2402-2480MHz	9dBm
	2412-2472MHz	13dBm
	5180-5320MHz	14dBm
WiFi	5180-5320MHz	14dBm
	5500-5825MHz	14dBm

For this radio device, the following restrictions on putting into service or of requirements for authorisation of use apply in BE, BG, CZ, DK, DE, EE, IE, EL, ES, FR, HR, IT, CY, LV, LT, LU, HU, MT, NL, AT, PL, PT, RO, SI, SK, FI, SE, UK, IS, LI, NO, CH, TR: 5150-5350 MHz band is restricted to indoor operations only.

FCC NOTICE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
•Reorient or relocate the receiving antenna.
•Increase the separation between the equipment and receiver.
•Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
•Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. The equipment should be installed and operated with minimum distance 20 cm between the radiator & your body.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

11